

# POWER TRANSFORMER CHASSIS MOUNT : TOROIDAL WORLD SERIES

# VPT36-1390

## **Electrical Specifications (@25C)**

- 1. Maximum Power: 50VA
- 2. Input Voltage: Series: 230VAC, 50/60Hz Parallel: 115VAC, 50/60Hz
- 3. Output Voltage: Series: 36VAC CT @ 1.39A Parallel: 18.0VAC @ 2.78A
- 4. Voltage Regulation: 12% TYP from full load to no load
- 5. Temperature Rise: 40°C TYP
- 6. Hipot: 4000VAC, Primary to Secondary
- 7. Efficiency: 86% TYP. @ full load

#### **Construction:**

The toroidal construction inherently helps reduce stray fields, increases efficiency and minimizes size compared to traditional EI transformers. Built with Class B (130°) insulation system.

#### Safety:

World Series Transformers are designed and manufactured to meet most International Safety agency standards.

#### Agency File:

- UL: File E122529, UL 506
- CE: EN 61558-1:2005, EN 61558-2-6:1995, Low Voltage Directive (LVD) EN 6-000-6-6:2001+A11:2004, EN 55014-1:2000+A1:2001+A2:2002, EN 6100-6-1:2001, EN 55014-2:1997+A1:2001, Electromagnetic Compatibility (EMC)



Dimensions (mm)

H*	I.D.	O.D.
33.0	25.0	80.0

\*Add 3mm to the height for mounting hardware Weight: 0.6Kg

### Mounting:

Transformer is provided with one metal mounting plate, two rubber pads, M5 x 45mm bolt, nut, spring and flat washer.

#### **Connections:**

Transformer is provided with 8" (200mm) long, 0.25" (6mm) stripped and tinned, stranded UL 1015 lead wire. Primaries are 22AWG, Secondaries are 20AWG.

- Input<sup>1</sup>: Series BLUE and BROWN, Jumper GRAY to VIOLET
- Parallel BLUE and BROWN, Jumper BLUE to VIOLET, GRAY to BROWN Output<sup>1</sup>: Series – BLACK and YELLOW, Jumper RED to ORANGE
  - Parallel BLACK and YELLOW, Jumper BLACK to ORANGE, RED to YELLOW

**RoHS Compliance:** As of manufacturing date February 2005, all standard products meet the requirements of 2011/65/EU, known as the RoHS initiative.

\* Upon printing, this document is considered "uncontrolled". Please contact Triad Magnetics' website for the most current version.

<sup>1</sup> Primary and secondary windings are designed to be connected in series or parallel. Windings are not intended to be used independently.

Web: www.TriadMagnetics.com Phone 951-277-0757 Fax 951-277-2757

460 Harley Knox Blvd. Perris, California 92571



