Fuseholders

For Micro™ Fuse or Pico® II Fuses

"Push-On" Retaining Nut Chassis Mount Type

QPL

Fuseholder will accept Littelfuse MICRO[™] fuses and PICO[®] II fuses (rated to 5 amperes) with .025" diameter leads.

SPECIFICATIONS:

Electrical: Rated at 5 amperes for any voltage up to 125 volts.

Mounting: Maximum panel thickness is .09".

Molded Parts: Black Thermoset.

Terminals: Beryllium Copper, Silver-plated. **Ambient Temperature:** -40°C to +125°C. **Hardware:** "Push-On" retaining nut.

* Please refer to Fuseology section for information on proper fuseholder de-rating.

FOR MICRO™ FUSE OR PICO® II FUSES

Vertical/Horizontal

P.C. Board Mount Type

Fuseholder will accept Littelfuse MICRO™ fuses and PICO® II fuses (rated to 5 amperes) with .025" diameter leads.

SPECIFICATIONS:

Electrical: Rated at 5 amperes for any voltage up to 125 volts.

Molded Parts: White Thermoplastic.

Terminals: Copper Alloy.


Ambient Temperature: -40°C to +100°C.

ORDERING INFORMATION:


Catalog Number	Terminal Plating	Mounting
281 005	Silver ¹	Vertical
281 008	Tin	Vertical
281 007	Silver ¹	Horizontal
281 010	Tin	Horizontal

¹UL Recognized.


281 001 Series "Push-On"








IR。







For LT-5™ and TR5® Fuses

P.C. Board Mount Type

See 560 Series holder for new designs and replacement.

SPECIFICATIONS:

Electrical: Rated at 5 amperes for any voltage up to 250 volts.


Molded Parts: Black Thermoplastic (UL94 V-O)

Terminals: The plate brasing gold side.

ORDERING INFORMATION:

Catalog Number: 023 0000

* Please refer useol proper fuseholder de-rating.



13

FUSEHOLDERS

^{*} Please refer to Fuseology section for information on proper fuseholder de-rating.